

Manufacture

MC-230

Upload FW:

FW HEMS G2 v1.0.0 RC

Power-meters

Modbus settings for power-meters we supply: **9600 8n2; ID: 149**

PM1-E-D

Factory setting: **2400 8n1; ID: 1**

Put power-meter in set mode by pressing button until **-SET-** is displayed on power-meter display.

Parameter	Address (hex)	Format	Default value (hex)	New value (hex)
Parity / Stop bits	40019 (00 12)	float	0 (00 00 00 00) = n1	3 (40 40 00 00) = n2
Meter ID	40021 (00 14)	float	1 (3F 80 00 00) = 1	149 (43 15 00 00) = 149
Baud Rate	40029 (00 1C)	float	0 (00 00 00 00) = 2400	2 (40 00 00 00) = 9600

CyBro-2-230-E configuring SW:

eastron_config.zip

PM3-I-D

Power-meters are supplied according to our specifications - no configuration needed before sending.

From: <https://wiki.hiq-universe.com/> -

Permanent link: https://wiki.hiq-universe.com/doku.php?id=en:hems:methods_resources:manufacture&rev=1538984121

Last update: 2018/10/08 07:35

