

Manufacture

MC-230

Upload FW:

FW HEMS v1.0.2

Power-sensors

Modbus settings for supplied power-sensors: **9600 8n2; ID: 149**

PM1-E-D

Factory setting: **2400 8n1; ID: 1**

Put power-sensor in set mode by pressing button until **-SET-** is displayed on power-sensor display.

Parameter	Address (hex)	Format	Default value (hex)	New value (hex)
Parity / Stop bits	40019 (00 12)	float	0 (00 00 00 00) = n1	3 (40 40 00 00) = n2
Sensor ID	40021 (00 14)	float	1 (3F 80 00 00) = 1	149 (43 15 00 00) = 149
Baud Rate	40029 (00 1C)	float	0 (00 00 00 00) = 2400	2 (40 00 00 00) = 9600

CyBro-2-230-E configuring SW:

eastron_config.zip

PM3-I-D

Power-meters are supplied according to our specifications - no configuration needed before sending.

From:
<http://wiki.hiq-universe.com/> -

Permanent link:
http://wiki.hiq-universe.com/doku.php?id=en:hems:methods_resources:manufacture&rev=1541427006

Last update: **2018/11/05 14:10**

