

# Serial converter

## RS232 to RS485 converter




Model number:	<b>CAD-232-A2-IQ</b>
Mounting:	DIN rail, 2M, 36 mm
Dimensions:	36x99x58 mm

## Applications

- Connecting power sensor and other RS-485 devices to HC/MC (Home Controller/Master Controller)

## Installation

-  Place CAD-232-A2-IQ module on DIN rail next to Home Controller
- Connect enclosed red cable between COM1 port on Home Controller and one of RS232 port at bottom side of CAD-232-A2-IQ module
- Connect RS485 terminals to SDM-120-C RS485 terminals
  - A - A
  - B - B
  - C - GND

## Features

- 2 x RS232 channel
- galvanic isolated A-bus lines from RS232
- LED signalization for data flow
- push and click mounting on DIN rail
- small dimensions
- removable RS485 terminal
- 24V DC powered over IEX-2 bus

## General description

**Power meter converter** is RS232 to RS485 converter used to connect [PM1-E-D](#) and other power sensors to Home Controller.

## Technical specification

Power supply:	24V/50mA
Galvanic isolation:	RS485 is galvanic isolated from circuit
Ingress protection:	IP20
Operating temperature:	0..50°C
Storage temperature:	-20..75°C
Relative humidity:	0..85% n/c

## Terminals

To power sensor	<b>A</b>	RS485 bus
	<b>B</b>	
	<b>C</b>	

From:  
<http://wiki.hiq-universe.com/> -

Permanent link:  
[http://wiki.hiq-universe.com/doku.php?id=en:hiq\\_hw:cad-232-a2-iq&rev=1632233835](http://wiki.hiq-universe.com/doku.php?id=en:hiq_hw:cad-232-a2-iq&rev=1632233835)

Last update: **2021/09/21 14:17**

