

# HARDWARE

SafeGate's hardware includes QR code and RFID card reader, TOF sensor, body temperature sensor and protective mask detector. The last two can be combined into face scanner.

## Wiring

Device	Power supply	Conected to	
TOF sensor	POE	MC	GND, IX0, IX1
Temperature and mask scanner	12 VDC	MC	GND, IX2
QR and RFID reader	+12V, GND	CR-W2	D0, D1-0, GN-0
Entrance allowed	-	CR-W2	C1 - QX0
REED entrance	-	CR-W2	GND - IW0
Button entrance	-	CR-W2	GND - IW1
Exit allowed	-	CR-W2	C2 - QX1
REED exit	-	CR-W2	GND - IW2
Button exit	-	CR-W2	GND - IW3
Motion sensor	+24V, GND	MC	IX0
Hand disinfection	-	MC	GND - IO14
Alarm	12 VDC	MC	QX0
LED Display	230 VAC	MC	TxD, RxD, GND

From:

<http://wiki.hiq-universe.com/> -

Permanent link:

<http://wiki.hiq-universe.com/doku.php?id=en:3s:hw&rev=1597043608>

Last update: **2020/08/10 07:13**

