

Motion sensor

Microwave detector on wall or ceiling



Model number:	MW-A18-SA
Connects to:	Lighting circuit
Mounting:	Wall or ceiling
Dimensions:	94mm x 42mm

Applications

- Motion detector
- Ready light
- Lighting control
- Hotel GRMS

Features

- Aestetical look
- Easy mount

Installation instruction

- Ensure that there are no obstructions (plants, screens, furniture etc.) in the field of view that may cause incorrect cover/operation of the detector.
- Install the detector at proper height on a rigid surface. Do not install the detector on vibrating surface.

Technical specifications

Power supply	230 VAC
Temperature	-20°C ~ 40°C
Humidity	< 93%
Range	2-18 m (Adjustable)
Installing height	Max. 3.5 m
Power frequency	5.8 GHz +/- 75MHz
Ambient light	10~2000LUX (Adjustable)
Detection	360 deg

Terminals

Power	L	Live
Signal	N	Neutral
Power supply	L OUT	Lighting circuit

From:

<https://wiki.hiq-universe.com/> -

Permanent link:

https://wiki.hiq-universe.com/doku.php?id=en:ms_main:mw-a18-sa

Last update: **2021/02/03 09:24**

