

Motion sensor

Microwave detector outdoor IP65 on wall or ceiling



Model number:	MW-A18W-SA
Connects to:	digital input
Mounting:	Wall or ceiling
Dimensions:	94mm x 42mm

Applications

- Outdoor motion detection
- Parking lights automation

Installation instruction

- Ensure that there are no obstructions (plants, screens, furniture etc.) in the field of view that may cause incorrect cover/operation of the detector.
- Install the detector at proper height on a rigid surface. Do not install the detector on vibrating surface.

Technical specifications

Power supply	230 VAC
Temperature	-20°C ~ 55°C
Humidity	< 93%
Range	2-18 m (Adjustable)
Installing height	Max. 3.5 m
Power frequency	5.8 GHz +/- 75MHz
Ambient light	10~2000LUX (Adjustable)
Detection	360 deg

Terminals

Power	L	Live
	N	
Lighting circuit	L OUT	Live out

From:

<http://wiki.hiq-universe.com/> -

Permanent link:

http://wiki.hiq-universe.com/doku.php?id=en:ms_main:mw-a18w-sa&rev=1612344498

Last update: **2021/02/03 09:28**

